


主线束(20)

CV10-20


M43 仪表盘扬声器
- 2母/白色(KUM_CDR_02F_W)




1. G 仪表盘
(扬声器(+)_输出)

2. O 仪表盘
(扬声器(-)_输出)


M44 中央扬声器(配备JBL)
- 2母/白色(KET_090II_02F_W_I)




1. W/B 放大器(+)

2. Br/B 放大器(-)

M45 模拟时钟
- 10母/黑色(MLX_FIT_10F_B)



1. G/O IGPM(LCAD保险丝-F17)

2. P IGPM(保险丝-F49)

3. L 照明灯(+)

4. -

5. Gr 照明灯(-)

6. -


7. R M-CAN(高电位)

8. L M-CAN(低电位)

9. -

10. B 搭铁(GM01)


M46 保安灯
- 2母/白色(KET_030_02F_W)



1. G/O IGPM(LCAD保险丝-F17)

2. G BCM(保安灯)

M47 起动/停止按钮开关
- 16母/白色(KET_040III_16F_W)




1. W 智能钥匙控制模块 (钥匙防盗搭铁)	9. Y/B 智能钥匙控制模块 (SSB LED OFF)
2. Y/O 智能钥匙控制模块 (SSB照明灯电源)	10. Gr/O 智能钥匙控制模块 (SSB LED蓝色)
3. B 搭铁(GM05)	11. Br 智能钥匙控制模块 (SSB LED琥珀色)
4. -	12. G 智能钥匙控制模块 (SSB 照明灯搭铁)
5. O/B 智能钥匙控制模块 (SSB开关2)	13. Gr 照明灯(-)
6. Br/B 智能钥匙控制模块 (SSB开关1)	14. R/B BCM(SSB环照明灯)
7. W/B IGPM(保险丝-F18)	15. -
8. L 智能钥匙控制模块 (钥匙防盗电源)	16. -