


车顶线束(1)

CV60-1

R01 车顶控制台灯


- 4母/白色(KET_070_04F_W)



- | | | | |
|--------|------------|------|---------------------------------|
| 1. B | 搭铁(GM01) | 3. L | 室内灯 |
| 2. Y/B | BCM(室内灯输出) | 4. R | 智能接线盒(暗电流
自动切断装置保险丝-
室内灯) |

R02 电镜后视镜


- 10母/黑色(SUM_025_10F_B)



- | | | | |
|---------|----------------|-------|--|
| 1. Gr/B | 远程信息处理模块(键盘信号) | 8. B | 搭铁(GM01) |
| 2. - | - | 9. | 倒车灯信号:
[A/T]发动机室保险丝&继电器盒
(保险丝-倒车灯) |
| 3. Br/O | 远程信息处理模块(键盘搭铁) | L | [M/T]倒车灯开关 |
| 4. - | - | L | 智能接线盒
(保险丝-模块2) |
| 5. - | - | 10. R | |
| 6. L/R | 照明灯(+) | | |
| 7. - | - | | |

R04 室内灯


- 3母/白色(KET_090II_03F_W)



- | | | | |
|------|---------------------------------|-----|--|
| 1. R | 智能接线盒(暗电流
自动切断装置保险丝-
室内灯) | 3. | [配备阅读灯]
车顶控制台灯(室内(+))
[未配备阅读灯]
BCM(室内灯输出) |
| 2. B | 搭铁(GM01) | Y/B | |

R05 天窗


- 10母/灰色(YAZ_1.5SYS_10F_GR_A)



- | | | | |
|--------|--------------------|--------|-------------------|
| 1. B | 搭铁(GM01) | 6. R | 智能接线盒
(保险丝-天窗) |
| 2. O | 天窗开关(信号A) | 7. L/B | BCM(天窗开启开关) |
| 3. O/B | 智能接线盒
(保险丝-模块5) | 8. - | - |
| 4. Y | 天窗开关(信号C) | 9. - | - |
| 5. - | - | 10. Gr | 天窗开关(信号B) |

R06 天窗开关


- 6母/黑色(AMP_MQS_06F_B)



- | | | | |
|-------|----------|------|---------|
| 1. B | 搭铁(GM01) | 4. Y | 天窗(信号C) |
| 2. O | 天窗(信号A) | 5. - | - |
| 3. Gr | 天窗(信号B) | 6. - | - |

R07 左梳妆灯

- 2母/黑色(AMP_PLM2_02F_B)



- | | | | |
|------|----------|------|---------------------------------|
| 1. B | 搭铁(GM01) | 2. R | 智能接线盒(暗电流
自动切断装置保险丝-
室内灯) |
|------|----------|------|---------------------------------|